



**SOS2**



**SOS2-6TC12150C**



**Features & Benefits**

The Power Battery SOS (Spares On Site) cabinet system provides users and service personnel immediate access to the exact battery they need in an emergency. The SOS cabinet eliminates the need to wait while a replacement battery is shipped in. Simply unplug the required battery from the SOS system and replace the suspect battery. No need to reschedule a service call or jump out a battery. The right spare battery is there when you need it most.

**Specifications**

- UL approved.
- Spare batteries always available on site.
- Battery matched to your system.
- Each SOS battery has its own quick disconnect.
- SOS cabinet plugs into a standard 120 VAC outlet.
- The charger will operate at 120/208/240 VAC 50/60 Hz.
- Cabinets are on casters for ease of mobility.
- Batteries are on continuous float charge, ready for service.
- Charger AC "ON" LED.
- SOS cabinets can be shipped with or without batteries installed.
- The 12 VDC charger operates with batteries in parallel.
- Using the chart, the SOS model number is created by combining the quantity and the model number of the batteries needed with the required cabinet. i.e. SOS1-3PRC12100S or SOS2-6TC12150C.
- A combination of various AH batteries can be combined into a single SOS cabinet.
- SOS cabinets for PM Series and large 2 volt batteries are available, contact factory.

BATTERY MODEL NUMBER	MAXIMUM NO. OF BATTERIES		WEIGHT LBS / KGS	
	SOS1	SOS2	SOS1	SOS2
PRC/TC-1225	6	12	204 / 93	408 / 185
PRC/TC-1235L	6	12	235 / 107	470 / 214
PRC/TC-1250S	4	8	216 / 99	432 / 196
PRC/TC-1265S	4	8	278 / 126	556 / 253
PRC/TC-1290S	4	8	317 / 144	634 / 288
PRC/TC-12100S	3	6	291 / 132	582 / 264
PRC/TC-12120S	3	6	321 / 146	642 / 292
PRC/TC-12150C	3	6	376 / 171	752 / 342
PRC/TC-6200S	2	6	239 / 108	623 / 283
PRC/TC-6225S	2	6	249 / 113	653 / 296

SOS CABINET MODEL	DIMENSIONS inches / millimeters		
	W	D	H
SOS1	34.5 / 876	16.0 / 406	17.75 / 451
SOS2	34.5 / 876	16.0 / 406	37.25 / 947

1420-1-0403